

Eco Wedge XT Solar Welcome Light

User Manual



- 10 Rawl Plug
- 2 Mountina Hole
- 3 Screw
- Solar Panel
- ⑤ On / Off Button and mode select

— .1. —

- @ PIR Motion Sensor

Technical Specifications:

Solar Panel: 0.55W

Li-ion battery: 3.7V 1200 mAh

LEDs: 0.8w, 6000K, 160 Lumens

Detection enabled: <10 Lux

Detection range: 120°, 3m

Light Modes:

- Off
- On with standard brightness
- On with Powersaving enabled

(motion detection enabled after dusk)

Size: 95 x 123 x 47mm

Operating the Light:

1. Installing the light

Please use the supplied wall plug and screw to mount the light unit on the wall.

2. Charging the light

A south facing wall is best for charging the light. Make sure the panel is not mounted behind glass or in the shade. Remove the protective film from the solar panel. Allow three days for the light to charge.

3. Activate the lamp

Use the on / off button on the front of the light to unlock the light ready for use.

1st push - standard brightness (160 lumens)


2nd push - Powersaving brightness (80 lumens)

3rd push - lamp is off.

4. Night sensor function

The motion sensor will activate the light when motion is detected and turn off approx 15 seconds after motion ceases.

Day / Night Cycle



Tips:



Ensure your solar panel is South facing or as near as possible



.5. —

Do **NOT** place your solar panel in shaded areas.

7

Clean your solar panel from time to time



Do **NOT** charge behind glass

Troubleshooting:

The Light is flashing

The light is running low on charge. Turn the light off and let it charge for 3 days with no activations to build up a good base charge in the battery.

— .2. —

The Light won't activate

If the light won't activate after dusk the light may be low on charge. Turn the light off and let it charge for 3 days with no activations to build up a good base charge in the battery.

Is there another light source hitting the panel, tricking it into thinking it's still daylight? Cover the panel with your hand to simulate total darkness, if light activates you may need to reconsider where the light is installed.

— .6. —

Package includes:

1. Eco Wedge XT Lamp 2. 1 x Wall Plugs

3. 1 x Screw

For customer support please contact:

The Solar Centre Ltd Unit 5, Dencora Centre Campfield Road St Albans Hertfordshire AL1 5HN

T: 0845 094 1250

W: www.solarcentre.co.uk

E: info@solarcentre.co.uk



Made in China to Solar Centre Specification



_____ .7. ____