

Selene Solar Landscape Spotlights



Ensure your solar panel is South facing or as near as possible



Clean your solar panel from time to time



Do **NOT** place your solar panel in shaded areas.



Do **NOT** charge behind glass


PLEASE CHARGE YOUR LIGHT FOR 3 DAYS BEFORE FIRST USE

User Guide

Thank you for choosing The Solar Centre's Selene Solar Landscape Spotlights. Please read these instructions carefully before using your lights.

Box Contents:

- 1 x Solar panel (a)
- 2 x Wall mounting bracket for the lights (b)
- 2 x Plastic poles (c)
- 2 x Stakes (d)
- 2 x Lights (e)
- 1 x Wall mounting bracket for the solar panel
- 6 x Screws and 6 rawl plugs



How it Works:

In the daytime the solar panel absorbs sunlight which charges the batteries. At night, with the switch set to on, the lights turn on automatically at dusk and turn off automatically at dawn. With the switch set to off the unit will not operate at any time.

Installing Your Panel and Lights:

When positioning your panel avoid locations where sunlight is obstructed by trees, foliage, buildings, fences or the shadows these create. A sunny South facing location is always ideal. Please note you have to situate each light within 5 metres of the solar panel. Once you have positioned your panel, adjust the tilt angle of the solar panel to ensure it collects as much sun as possible. Once you are totally satisfied with the location and positioning of your panel, position the lights where required using the stake or wall/deck mounting options. Turn the switch to on by pressing the power button on the underside of the solar panel. The lights will then turn on at dusk. **Please note that a poorly positioned panel will stop the lights illuminating for long after dark.**

Stake Mounting:

- 1: Connect the pole to the light head.
- 2: Locate the included stake fitting and connect that to the other end of the pole.
- 3: Place in the ground.

Wall Mounting:

When wall mounting the Landscape Spotlights it is particularly important to think about the amount of light the panel will receive in your proposed location. Where possible mount the panel on a south facing wall, fence or roof.

- 1: Locate the panel wall mounting bracket, mark and then drill holes into your desired location. Affix the panel using the screws and rawl plugs provided.
- 2: Mount the lights within 5 metres of the panel using the wall brackets. Mark and then drill holes affixing the lights using the rawl plugs and screws.

Changing the Batteries:

The batteries should last for up to 2 years.

- 1: Remove the screws on the underside of the solar panel.
- 2: Remove the underside.
- 3: Remove the batteries and replace with 3 x 1.2V AA 2000mAh Ni-MH batteries.
- 4: Please recycle the old batteries.

Troubleshooting:

1: The light is dim or flashes

Batteries are not fully charged or may need replacing.

The solar panel needs bright light to recharge the batteries. Consecutive days of overcast weather may cause the batteries to lose power. If this happens the solar panel will recharge the batteries on the next bright day.

Check your solar panel is in an area where it gets the maximum amount of direct light every day.

Check for things obstructing light reaching the solar panel like over hanging branches, fences or buildings. If there are obstructions move the unit to a location that receives better light throughout the day.

Check the solar panel is clean. A dirty solar panel will not let the batteries charge fully. This will shorten the life of the batteries and stop the light operating. Clean the solar panel regularly with damp cloth.

2: The light won't turn on

Check for an external light source like a street light or porch light, this may be stopping the light sensor from knowing when it is dark. Move the panel away from the external light source.

Rechargeable batteries may need charging, overcast weather could have prevented the batteries from recharging. Check to see if it works after the next sunny day.

After checking these problems observe the light after dark, if it still does not work then please contact us via the details below.

Recharge Procedure

Please follow the recharge procedure if the batteries in your Solar Landscape Spotlights run flat. Please turn off your Solar Landscape Spotlights using the switch on the underside of the solar panel unit and place them outside in a sunlit location for 5 days to gain a base charge. Ensure that the light hitting the solar panel is not obstructed in anyway. This is particularly important in winter when the days are shorter and the sun is lower in the sky and less powerful. Please note that your Solar Landscape Spotlights will not charge behind glass.

For customer support please contact:

The Solar Centre Ltd
Unit 5, Dencora Centre
Campfield Road
St Albans
AL1 5HN

T: 0845 094 1250

W: www.thesolarcentre.co.uk

E: info@thesolarcentre.co.uk



Made in China to Solar Centre Specification